

Model 2140



Optical Mini Bit-Driver



Meets FCC requirements of Class A, Part 15 Computing Devices Standard.



Features:

- RS-422/485 Multipoint operation with up to 32 nodes
- Various speeds 110 bps to 230 Kbps, 4 Wire (Speed set at the factory)
- Flange Mounting
- Multimode or single mode options
- Repeater with 4-wire RS-422/485 Add/Drop

Fiber ports repeat data through the 2140 and drop/insert data on the RS-422/485 port. The RS-422/485 port inserts data onto both fiber ports and drops data from both fiber ports.

RS - 422/485 CONNECTOR

| Pin No. | Description | DB-9 Female Pin | RS - 422/485 CONNECTOR |
|---------|-------------|-----------------|------------------------|
| 1 | R+ (Input) | 4 | |
| 2 | R- (Input) | 6 | |
| 3 | T+ (Output) | 3 | |
| 4 | T- (Output) | 9 | Pin 1 2 3 4 |
| | Ground | 1, 5 | |

OPERATING DISTANCE FOR FIBER OPTIC CABLE


| Fiber Size | Attenuation | Distance | Distance |
|------------|-------------|----------|----------|
| (Microns) | dB/Km | Meters* | Feet* |
| 50 | 3.0 | 2000 | 6600 |
| 62.5 | 4.0 | 2000 | 6600 |
| 10 SM | 1.0 | 10000 | 33000 |

* High power option available (20dB)

SM - Single Mode (1300nm). Temp: SM -20^o to +60^o C

ORDERING INFORMATION

| Model Number | Description | |
|--------------|--|--|
| 2140-MM-B | Multimode to One side blank, ST Connectors | |
| 2140-MM-MM | Multimode to Multimode, ST Connectors | |
| 2140-MM-SM | Multimode to Single Mode, ST Connectors | |
| 2140-SM-SM | Single Mode to Single Mode, ST Connectors | |



For application engineering assistance: 630-761-3640 FAX: 630-761-3644 S.I.Tech, P.O.Box 609, Geneva, Illinois 60134 U.S.A. Web site: http://www.sitech-bitdriver.com. © 2013 S.I. Tech, Inc.